

150W Magnetic Low Voltage Transformers

Features

- Compatible with Non-Linear LED driver/lamp loads, and traditional incandescent loads.
- Line dimming may be achieved with Magnetic Low Voltage (MLV) type dimmers.
- Optional boost tap included on 120Vac models raises output voltage by 10%.
- Output short-circuit and overload protection (13A) with manual-reset circuit breaker.
- Auto-reset input circuit protection.
- All stainless steel chassis construction.
- 5-Year Warranty



Model Numbers & Specifications

Model	Input Voltage	Max. Input Current	Output Voltage	Max. Output Current*	Max. Wattage
PS20B150M	120Vac 60Hz.	1.33A	12Vac	13A	150W
PS20D150M	277Vac 60Hz.	0.62A	12Vac	13A	150W

* Transformers over 300-Watts will be configured with 2 or more breakers per N.E.C.

Mechanical & Environmental

- Class B (130°C) Insulation system
- Operating Temperature -30°C to 105°C
- Input leads are UL1015 # 18 AWG, rated 105°C
- Output leads are UL1015 # 16AWG, rated 105°C
- Unit weight is 6.4 Lbs.
- Epoxy encapsulated transformer
- NEMA 3R AISI 304 Stainless Steel enclosure
- Wiring compartment opens vertically with hinged door
- Wiring compartment (bottom) has three 1/2" knock-outs
- UL Listed for the US and Canada, File E362033

Enclosure Dimensions

